



## A . Features

- 5.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

## B . Operational Manual

1. At any state ,press A key EL backlight for 3s .
2. In Real Time Mode,press B key once displaying Date
3. **Time Setting**
  - In Real Time Mode ,Press C key once to entry Time Setting mode ,select item in turn as following :  
Second → Hour → Minute → Month → Day
  - Press B key to adjust the flashing item
  - As setting seconds,the flashing seconds can be reset to zero by pressing B key and will return back to Real Time Mode automatically.
  - Press B key while the seconds are in the range of 30 to 59 resets them to 00 and adds 1 to the minutes . In the range of 00 to 29,the minutes are unchanged.

## C. Specifications

- Module Size : 28.20\*28.20mm
- Module Thickness : 3.10 mm
- Operational Temperature Range : -10°C~60°C
- Operational Voltage : 1.5V
- Accuracy : ± 60sec/month
- Battery Code : V371MF(capacitance: 35m Ah)
- static average current : ≤0.98u A (static maximum current : 2.5uA)
- EL lighten average current : ≤8.30m A (ELlighten maximum current : 10mA)
- Battery life (90%) : ≥18 month

(Battery life calculate according to EL lighten four time each day for 3 second each time.)

	Prepared	Checked	Approve
Name	冯碧颜	徐治中	宋检望
Date	11/04/11	11/04/11	11/04/11