



—— ( B Key ) MODE

—— ( A Key ) SET

## A . Features

- 3.5 Digits LCD Display, Display Hour ,Minute ,Second ,Month and Day .

## B . Operational Manual

1. At time setting mode ,press B key to activate auto advance function.
2. press B key once displaying Date ;twice displaying Second , Press B key again to return to Real Time mode .

### 3. TIME SETTING

- Press A key twice to entry Time Setting mode ,select item in turn as following :  
 Month → Day → Hour → Minute
- Press B key to adjust the flashing item.
- Press A key to confirm.

## C. Specification

- Dimension : 30.60\*27.30mm
- Thickness (exclude buzzer) : 3.90mm
- Working temperature : -10℃~+60℃
- Working voltage : 1.5V
- Time accuracy : ±60S/Month
- Battery type : V373 RENATA ( Capacity:29mAh)
- Average Static current : ≤1.69u A (Maximum static current: 2.5 u A)
- Battery Life (90%) : ≥18 Months

	Prepared	Checked	Approved
Name	冯碧颜	徐治中	宋检望
Date	11/11/23	11/11/23	11/11/23